

# DIGITAL Zip-Set™ Time Switch

## Astronomic Digital Control SA300 Series



### APPLICATIONS

- Outdoor lighting.
- Electric motors.
- Indoor lighting or signs.

### FEATURES

- Zip-Set: Fast and easy. Just enter area code and timer adjusts to your time with preset program of Sunset ON and time off program.
- Scheduling: One On/Off set point pair is active at a time. Only one schedule may be active at a time: Schedule 1, Schedule 2, a combination of 1 & 2, or ZipSet™. Day combinations for 7-5-2 speed programming.
- Manual Daylight Saving: Simple switch adjustment.
- Manual Override: Until the next regularly scheduled ON or OFF, automatic operation then resumes.
- Random Feature: Varies on time +/-90 minutes each day for lived in look.
- Clock Format: AM/PM.
- Power Outage Backup: Replaceable batteries



CAT. NO.	UPC CODE	INPUT SUPPLY (VAC) 50-60Hz	OUTPUT CONTACTS
SA300	16546	120	SPST
SA306	16549	120	DPST
SA400	16552	120/277	SPST

### SPECIFICATIONS

- Input Voltage: 120VAC, 60Hz  
- SA400 120/277VAC, 60Hz
- Terminal Range: #8 - #16AWG.
- Operating Temperature: 32 °F to +100 °F (0 °C to +37 °C).
- Power Consumption: 5VA Max.
- Enclosure: Indoor Metal with locking hasp.  
SA400 Outdoor Metal with locking hasp.  
(See Pages 464-468 For Dimensions).

### WIRING DIAGRAMS

- See Pages 377-388 For Diagrams.

TYPE	VOLTAGE (VAC) 60Hz	RATING
Resistive	120*	40A
Inductive	120*	40A
Tungsten	120*	40A
Incandescent	120*	40A
Motor	120	1 1/2HP
*SA400	120/277	